

## Support 4k\*2k HDMI Splitter 1x8

This 1x8 HDMI Splitter that supports Full HD 3D&4Kx2K uses a single HDMI source, accessing to multiple HDMI sinks. The Splitter allows one HDMI devices to be split easily to 8 HDMI compatible monitors or projectors. The Splitter can also be placed at the end of along HDMI cable to regenerate the HDMI signal. This HDMI splitter 1x 8 distributes 1 HDMI source to 8 HDMI displays simultaneously. It offers HD video solution for super market; shopping mall; HDTV, STB, DVD, projector factory; data control center; information distribution; conference room presentation; education and training; corporation show room; home theater, etc.

### Feature

- One HDMI 1.4a input signal split to eight HDMI 1.4a sink devices
- Support 4K\*2K resolution
- Support 3D
- Support CEC
- Support HDCP
- Support deep color 30bit, 36bit, 48bit
- Support Blue-Ray 24/50/60fs/HD-DVD/xvYCC
- Digital audio format, as  
DTS-HD/Dolby-trueHD/LPCM7.1/DTS/Dolby-AC3/DSD/HD(HBR)
- Support signal retiming
- Support input up to 10metres AWG26 HDMI standard cable length,  
Output up to 10metres AWG26 cable length
- No loss of quality
- Installs in minutes
- Need DC5V/3A power supply

### Specification

HDMI version	HDMI 1.4v
HDCP version	HDCP1.3
HDMI resolution	24/50/60fs/1080p/1080i/720p/576p/576i/480p/480i
Support video color format	24bit/deep color 30bit,36bit
Support audio format	DTS-HD/Dolby-trueHD/LPCM7.1/DTS/Dolby-A C3/DSD
Max bandwidth	225MHz
Max baud rate	6.75Gbps
Input/Output TMDS signal	0.5~1.5Volts p-p(TTL)
Input/Output DDC signal	5Volts p-p (TTL)

Input cable distance	<=15m AWG26 HDMI standard cable
Output cable distance	<=25m AWG26 HDMI standard cable
Max working current	2.0A
Power adapter format Input	AC (50HZ, 60HZ) :100V-240V; Output: DC12V/2A
Operating Temperature range	(-15 to +55 Centigrade)
Operating Humidity range	5 to 90%RH (No Condensation)
Dimension (L x W x H)	380x140x60 (mm)
Weight	2030g

**Package accessory:**

One HDMI Splitter 1x8

One User Manual

One Power Adapter - 100-240V, 5V Output

**Notes:**

Pls use the machine as the instruction listed to keep the long use lifetime of the machine.

- 1.The machine should be placed at the spot far from the Damp, High-Temperature, Dusty, Erosive, and oxidative environment.
- 2.All parts will be free from the strong shake, hit, fall.
- 3.Touching the power adaptor with the wet hands is prohibited.
- 4.Pls hold the power adaptor head and do not pull the power cord when cut off from the socket.
- 5.Pls turn the power off when the machine is not used for long time.
- 6.Pls do not open the cover and do not touch the inside parts.
- 7.Pls use the original factory power adaptor.