

4Port HDMI KVM Switch



Model: DK34

The HDMI KVM Switch with built-in sound effect function. It is specially designed for users of PC and Mac with built-in HDMI interfaces and loyal fans of SOHO environment and technology, which is well-suited for HDMI. This unique type of KVM switch can easily control two computers, which have built-in HDMI interfaces, via a HDMI display and either a PC or Mac keyboard and mouse. Image distortion due to conversion of analog and digital signals will not be a problem anymore.

This KVM switch controls multiple PCs from one keyboard, mouse and HDMI monitor.

Features:

1. One USB or PS/2 console controls 2 HDMI-interface computers
2. Switch model: via front panel pushbuttons and hotkeys
3. HDMI digital monitor support-fully compliant with HDMI 1.3a; also HDCP compliant
4. Superior video quality-supports 480i,480p,720p,1080i,and 1080p(HDTV)/1920X1200(DVI)
5. Support Hot plug&play
6. Support widescreen resolutions
7. OS support-Windows, Linux, and Mac

8. Auto Scan Mode for monitoring all computers and HDMI devices.

Specifications

Computer Connections		4	
Port Selection		Front Panel Pushbuttons; Hotkeys	
Connectors	Console Ports	Keyboard	1 X USB Type A Female
		Video	1 x HDMI Type A Female
		Mouse	1 x USB Type A Female
	KVM Ports	Keyboard / Mouse	4 USB Type B Female
		Video	4 HDMI Type A Female
	Power	1 xDC Jack	
Switches	Selected	4 Push button	
Emulation	Keyboard/Mouse	USB	
Video		1080p (HDTV) / 1920 脳 1200 (DVI)	
Scan Interval		10 seconds.	
Power Consumption		DC 5V	
Environment	Operating Temp.	0-50	
	Storage Temp.	-20-60	
	Humidity	0-80% RH, Non-condensing	
Physical Properties	Housing	Metal	
	Weight	0.7kg	
	Dimensions (L x W x H)	254x100x44 mm	

Switching Operation Instructions

1.Push botton

Simply press the appropriate port selection switch on the front panel. After you press the switch, the select LED lighting indicate that the port is selected currently.

2.HOT KEY

Hot Key allows you to conveniently to access connected PCs directly from the keyboard, instead of having to manually select them by pressing port selection switches. To select a port with the hot key method, do the following:

- 1) [Scroll Lock] + [Scroll Lock]+ 1/2/3/4/5/6/7/8 +[Enter]
- 2) Auto Scan function: [Scroll Lock] + [Scroll Lock]+S+[Enter]