

# 8 port HDMI KVM switch



Model: DK35

## Features

1. One USB or PS/2 console controls 8 HDMI-interface computers;
2. Switch Mode: a. button push b. Keyboard Hot-Key switch;
3. HDMI digital monitor support - fully compliant with HDMI 1.4a; also HDCP compliant;
4. Superior video quality - supports 480i, 480p, 720p, 1080i, and 1080p(HDTV)/1920 x 1200(DVI);
5. Support Hot plug & play;
6. Supports widescreen resolutions;
7. OS support - Windows, Linux, and Mac;
8. Auto Scan Mode for monitoring all computers and HDMI devices.

## Specification

Computer Connections		8	
Port Selection		Front Panel Pushbuttons; Hotkeys	
Connectors	Console Ports	Keyboard	1× USB Type A Female
		Video	1× HDMI Type A Female
		Mouse	1× USB Type A Female
	KVM Ports	Keyboard / Mouse	8 USB Type B Female
		Video	8 HDMI Type A Female
Power		1×DC Jack	
Switches	Selected	Push button	
Emulation	Keyboard/Mouse	USB	
Video		1080p (HDTV) / 1920×1200 (DVI)	
Scan Interval		10 seconds.	
Power Consumption		DC 5V	
Environment	Operating Temp.	0-50°C	
	Storage Temp.	-20-60°C	
	Humidity	0-80% RH, Non-condensing	
Physical Properties	Housing	Metal	
	Weight	1.27kg	
	Dimensions (L x W x H)	428×100×44mm	

## Switching Operation Instructions

### 1.Push button

Simply press the appropriate port selection switch on the front panel. After you press the switch, the select LED lighting indicate that the port is selected currently.

### 2.HOT KEY

Hot Key allows you to conveniently to access connected PCs directly from the keyboard, instead of having to manually select them by pressing port selection switches. To select a port with the hot key method, do the following:

[Scroll Lock] + [Scroll Lock]+ 1/2/3/4/5/6/7/8 +[Enter]

Auto Scan function: [Scroll Lock] + [Scroll Lock]+S+[Enter]

## Connection and operating:

